

Three Phase Inverters for Residential Installations for Australia

SE5K-AUB / SE7K-AUB / SE8.25K-AUB / SE10K-AUB

INVERTERS



Three Phase Hybrid Inverter

The ideal solution for residential PV installations

- / Provides maximum design flexibility, enabling fewer, longer strings
- / Battery ready – one inverter for both PV and battery storage
- / Supports optional smart energy devices and expansion of system capabilities
- / Single vendor solution for seamless operation of all system components, and one address for warranty and service issues
- / Built-in module-level monitoring for greater visibility into system performance
- / Excellent reliability with standard 12-year warranty (extendable to 20 or 25 years)
- / Advanced safety features, including SafeDC™ beyond just PV and integrated arc fault protection
- / Quick inverter commissioning directly from a smartphone using SolarEdge's SetApp
- / Suitable for outdoor or indoor installations

solaredge.com

solaredge

/ Three Phase Inverters for Residential Installations for Australia

SE5K-AUB / SE7K-AUB / SE8.25K-AUB / SE10K-AUB

	SE5K-AUB	SE7K-AUB	SE8.25K-AUB	SE10K-AUB	
APPLICABLE TO INVERTERS WITH PART NUMBER					
SEXKX- AUBTXBNU4					
OUTPUT					
Rated AC Power Output	5000	7000	8250	10000	VA
Maximum AC Power Output	5000	7000	8250	10000	VA
AC Output Voltage - Line to Line / Line to Neutral (Nominal)	400 / 230				Vac
AC Output Voltage - Line to Neutral Range	184-264.7				Vac
AC Frequency	50 ± 5%				Hz
Maximum Continuous Output Current (per Phase)	8	11.5	13.5	16	A
Grids Supported - Three Phase	3 / N / PE (WYE with Neutral)				
Utility Monitoring, Islanding Protection, Configurable Power Factor, Country Configurable Thresholds	Yes				
INPUT					
Maximum DC Power (Module STC)	6750	9450	11135	13500	W
Transformer-less, Ungrounded	Yes				
Maximum Array Input Voltage	450				Vdc
Maximum Voltage to Earth (DC to GND)	450				Vdc
Maximum Input Current	14	19.5	22	28	Adc
Reverse-Polarity Protection	Yes				
Ground-Fault Isolation Detection	350kΩ Sensitivity				
Maximum Inverter Efficiency	97.8				%
European Weighted Efficiency	96.3	97	97.1	97.4	%
Nighttime Power Consumption	< 4				W
ADDITIONAL FEATURES					
Supported Communication Interfaces ⁽¹⁾	2 x RS485, Ethernet, Wi-Fi ⁽²⁾ , ZigBee for Smart Energy (optional) ⁽³⁾				
Inverter Commissioning	With the SetApp mobile application using built-in Wi-Fi access point for local connection				
Smart Energy Management ⁽⁴⁾	Export Limitation, Home Energy Management (Device Control)				
STANDARD COMPLIANCE					
Safety	IEC62109, AS/NZS3100				
Grid Connection Standards	AS/NSZ 4777.2:2015, EN 50549-1				
Emissions	IEC61000-6-2, IEC61000-6-3, IEC61000-3-11, IEC61000-3-12				
RoHS	Yes				

(1) Refer to Datasheets -> Communications category in Downloads page for specifications of optional communication options: <http://www.solaredge.com/groups/support/downloads>

(2) Wi-Fi connectivity requires connection of an additional Wi-Fi component, ordered separately. For more details ask your SolarEdge sales person or refer to: <https://www.solaredge.com/aus/products/communication>

(3) For more information refer to: <https://www.solaredge.com/sites/default/files/se-zigbee-plug-in-wireless-communication-for-setapp-datasheet-au.pdf>

(4) An export meter is required for export limitation and most of home energy management functions

/ Three Phase Inverters for Residential Installations for Australia

SE5K-AUB / SE7K-AUB / SE8.25K-AUB / SE10K-AUB

	SE5K-AUB	SE7K-AUB	SE8.25K-AUB	SE10K-AUB
INSTALLATION SPECIFICATIONS				
AC Output Conduit Size / Wire Cross Section	20mm minimum / 3-13mm ²			
DC Input Conduit Size / Wire Cross Section	20mm conduit size minimum			
DC Input	Single DC terminal block			
Dimensions with Safety Switch (H x W x D)	775 x 315 x 260			mm
Weight	30			kg
Operating Temperature Range	-40 to +60 ⁽¹⁾			°C
Cooling	Fan (user replaceable)			
Noise	< 50			dBA
Protection Rating	IP65 - outdoor and indoor			
Mounting	Bracket provided			
Number of Power Optimisers per String	8 ⁽²⁾ /9 to 25			
Maximum Power per String	5625			W

(1) For power de-rating information refer to: <https://www.solaredge.com/sites/default/files/se-temperature-derating-note.pdf>

(2) When using P404/P485/P505 power optimisers only, minimum required per string is eight



© SolarEdge Technologies, Inc. All rights reserved. SOLAREEDGE, the SolarEdge logo, OPTIMIZED BY SOLAREEDGE are trademarks or registered trademarks of SolarEdge Technologies, Inc. All other trademarks mentioned herein are trademarks of their respective owners. Date: 09/2020/V01/ENG AUS. Subject to change without notice.

